DATASHEET - PFR-5



Earth-leakage circuit-breaker 0, 03-5 A

Part no. PFR-5 Catalog No. 285557

EL-Nummer (Norway) 4365085



Delivery program

Rated fault currents	I $_{\Delta n}$	Α	0.03, 0.1, 0.3, 0.5, 1, 3, 5
Description			Adjustable fault current and delay time Fault current early warning by flashing, red LED Pulse-current sensitive Integrated auxiliary contact (1 C/O) Ring-type transformer must also be ordered not UL/CSA approved
Rated control voltage	Us	V	230 V AC 50/60Hz

Notes

Adjustable fault current: 0.03, 0.1, 0.3, 0.5, 1, 3, 5 A

Adjustable delay time: 0.02, 0.1, 0.3, 0.5, 1, 3, 5 A

Technical data

	ectr	ioo
ы	E GU	ıva

Operation

		IEC/EN 60947-2, IEC 755, IEC 1008, IEC 1009
		Pulse current sensitive, type A
U_s	V AC	230 ±20 % (50/60 Hz)
P _e	W	3
I $_{\Delta n}$	Α	0.03, 0.1, 0.3, 0.5, 1, 3, 5
t_{V}	s	0.02, 0.1, 0.3, 0.5, 1, 3, 5
		1 integrated changeover contact
	V AC/DC	250/100
	Α	6
	mm	45
	mm	85
	mm	45
		Snap fixing, top-hat rail DIN 46277, IEC/EN 60715
		Box terminals
		Finger/back-of-hand proof to BGV A2, VDE 106 part 100
	mm^2	2×0.75 - 2.5 solid, 2×0.75 - 1.5 flexible/with ferrules
		Setting buttons
	P _e I _{Δn}	P _e W I Δn A t _v s V AC/DC A mm mm mm

Design verification as per IEC/EN 61439

°C	-10
°C	50
	Meets the product standard's requirements.
	Does not apply, since the entire switchgear needs to be evaluated.
	-

°C

-10 - +50

10.2.6 Mechanical impact	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions	Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES	Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances	Meets the product standard's requirements.
10.5 Protection against electric shock	Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components	Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections	Is the panel builder's responsibility.
10.8 Connections for external conductors	Is the panel builder's responsibility.
10.9 Insulation properties	
10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
10.10 Temperature rise	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must observed.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 7.0

Low-voltage industrial components (EG000017) / Residual current release for power circuit breaker (EC001021)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Fault current switch for circuit breakers (ecl@ss10.0.1-27-37-04-11 [AKF009013])

[[711 000010]]		
Rated control supply voltage Us at AC 50HZ	V	184 - 276
Rated control supply voltage Us at AC 60HZ	V	184 - 276
Rated control supply voltage Us at DC	V	0 - 0
Rated fault current	Α	0.03 - 5
Max. power on-delay time	ms	5000
Delay adjustable		Yes
Max. rated operation voltage Ue	V	276

44

68

73

36

Fixing on TH35 top-hat rail to IEC/EN 60715