

PRODUCT DATASHEET ST 111 LONGLIFE

Starters for single operation at 230 V AC (ST 111, ST 171, ST 173) | Starters for single operation at 230 V AC

OSRAM .40L ade in PRC 180°C

Product features

- Temperature range for reliable cut-out: -20...+80 °C



May 31, 2023, 00:16:32 **ST 111 LONGLIFE**

TECHNICAL DATA

Electrical data

| Nominal wattage | 65.00 W | |
|-----------------|----------|--|
| Nominal voltage | 220240 V | |
| Mains frequency | 50/60 Hz | |

Dimensions & Weight

| Diameter | 21,5 mm |
|----------------|---------|
| Product weight | 6.58 g |

Lifespan

| Lifespan 0 relevant |
|---------------------|
|---------------------|

Additional product data

| Mercury content | 0.0 mg | |
|-----------------|--|--|
| Product remark | Not suitable for L 70 W / Starters are available in two different designs, with identical technical features | |

Capabilities

| Dimmable No | |
|-------------|--|
|-------------|--|

Country-specific categorizations

| Order reference | ST 111LL/220-24 |
|-----------------|-----------------|

Energy labelling regulation data acc EU 2019/2015

| Length | 40.30 mm |
|--------|----------|
| Height | 21,5 mm |
| Width | 21.50 mm |

DOWNLOAD DATA

| | DOWNLOAD DATA |
|-----|-------------------------------|
| PDF | Declarations Of Conformity CE |

LOGISTICAL DATA

| Product code | Packaging unit (Pieces/Unit) | Dimensions (length x width x height) | Gross weight | Volume |
|---------------|------------------------------|--------------------------------------|--------------|----------|
| 4050300854045 | Unpacked 1 | 37 mm x 19 mm x 21 mm | 6.58 g | 0.01 dm³ |
| 4050300797861 | Tray 25 | 111 mm x 41 mm x 111 mm | 180.50 g | 0.51 dm³ |
| 4050300797878 | Shipping box 400 | 227 mm x 179 mm x 227 mm | 3009.00 g | 9.22 dm³ |

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

DISCLAIMER

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.